

HYCON HPP18E FLEX REMOTE POWER PACK



REMOTE START/STOP

REMOTE STEPLESS FLOW REGULATION

EMISSION-FREE



PRODUCT FEATURES

The HYCON HPP18E FLEX REMOTE was designed for tasks requiring the remote operation of the power pack.

The drive allows you to start and stop, step-less vary the flow between 10 and 46 lpm (3 to 12 GPM), and engage the emergency stop from the remote with a standard wire length of 10 meters. This makes it ideal for many specialized jobs.

This power pack's 13.2 kW electric engine gives you enough power to operate most of our product range. It is also completely emission-free, which allows you to comply with stricter health and safety requirements.

Use the power pack outdoors in all kinds of weather or work indoors where a gasoline or a diesel engine cannot be used due to emission.

HYDRAULIC POWER PACK HPP18E FLEX REMOTE



Item no.	2020311
Oil flow [LPM / GPM]	10 - 46 / 3 - 12*
Working pressure [bar / psi]	120 / 1750
Max pressure [bar / psi]	160 / 2320
Hydraulic oil tank capacity [l / gal]	11 / 2.9
Electrical motor	Hoyer HMA3 132M2 (13.2 kW)
Electrical supply [V - Hz]	3 x 400 - 50 / 3 x 480 - 60
Ampere required [400V 50Hz / 480V 60Hz]	35 / 25
Dimensions L x W x H [mm / inch]	805 x 625 x 704 / 32 x 25 x 28
Weight [kg / lbs]	155 / 298
Sound power level LWa [dB]	99

*) Stepless variable

THE HYCON PRODUCT RANGE

CUT-OFF AND RING SAWS · CORE DRILLS · POST DRIVERS · PICK HAMMER · LIGHT & HEAVY DUTY BREAKERS
SUBMERSIBLE PUMPS · ROCK DRILLS · UNDERWATER EQUIPMENT · GASOLINE, DIESEL AND ELECTRIC POWER PACKS



HYCON A/S
Juelstrupparken 11
DK-9530 Støvring

Tel.: +45 9647 5200
Mail: hycon@hycon.dk
www.hycon.dk

DISTRIBUTOR: